

Magswitch Technology, Inc. 1355 Horizon Ave Lafayette, CO 80026 Magswitch.com.au 303-468-0662

Magswitch HLF-8000-M Three Ton P/N: 8800432


If you lift pipe, I-beams or heavy sheet steel, this is a tool you need in your shop! Magswitch Technology is "changing the way things are done" once again by introducing the innovative new Heavy Lift Frame Series. This game-changing tool utilizes patented Magswitch Technology to lift a single sheet from a stack of 3/4 in (19.05 mm) material. Enhanced workplace safety is achieved through fail safe operation. Increased strength, efficiency and durability make tough jobs easy. By providing unique magnetic solutions for new standards of productivity, one man can easily do the work of two. Safely lift up to 8,000 lbs of pipe, beam or flat sheet... experience Magswitch Technology today!






WARNING! Do Not Operate Unless In Contact With Ferrous Target


SPECIFICATIONS	
P/N: 8800432 – HLF-8000-M Three Ton	
Max SWL 3:1 Lift Capacity*	6,000 lbs/2727 kg
Minimum De-Stack Thickness	0.75"/ 19.05mm
Magnet Specification	MLAY1000x6
Quantity of Magnets	3
Frame Length	116" / 2.94m
Frame Width	30.5" / 0.78m
Frame Height	22.5" / 0.571m
Net Weight	460 lbs/208.7 kg
Frame Lifting Locations	Under Hook and Fork Pockets Available





^{*} Max Breakaway determined in laboratory environment on 2" thick SAE1018 Steel with surface roughness 63 micro inches. Many factors contribute to the actual breakaway force in each application. Always test the magswitch in each application before deployment. Refer to the magswitch information booklet for more information.



Note: Graph above shows performance of single tool. Heavy Lift Frame Series utilizes multiple magnets so consider number of tools when determining the capability of the tool.







* Max Breakaway determined in laboratory environment on 2" thick SAE1018 Steel with surface roughness 63 micro inches. Many factors contribute to the actual breakaway force in each application. Always test the magswitch in each application before deployment. Refer to the magswitch information booklet for more information.